

Residential/Light Commercial Generator Accessories

KOHLER Power Systems

Battery Heater Kits

ISO 9001
KOHLER
POWER SYSTEMS
NATIONALLY REGISTERED



Battery Heater Kit
with Wrap and Pad, Typical



Battery Heater Kit
with Wrap, Typical

Applicable Models

- 8.5/12/17/18RES/RESL
- 8/10/12RESV/RESVL
- 14/20RES/RESL
- 14/20RESA/RESAL, 120 Volts
- 14/20RESA, 240 Volts
- 15/30RES/RESA
- 15/30RYG/REYG
- 20RESB
- 20RESC/RESCL, 120 Volts
- 20RESC, 240 Volts
- 20RESD
- 24/30RCL
- 38/48/60RCL
- 38RCLB
- 40-150ERES (includes ERESB, ERESC, and ERESD)

Description

The battery heater kit includes a battery heating wrap to help increase the battery temperature in cold climates. Some kits also include a heating pad to install under the battery. The battery heaters are connected to a thermostat for controlled heating. When temperatures fall below 18°C (65°F), the thermostat activates the battery heaters, maintaining optimum battery temperature. The thermostat turns the heater off at 27°C (80°F).

Battery heater kits are recommended for generators installed in regions where the temperature regularly falls below 0°C (32°F).

Specifications

| Kit Numbers | GM79481-KP1 | PA-352359 | GM89021-KP1 | GM89022-KP1 | GM92406-KP2-QS | GM92406-KP3-QS |
|-------------------------------|-----------------------------------|-----------------------|---------------------------------|---|------------------------------------|--|
| Models | 24/30RCL 38/48/60RCL 38RCLB | 40-150ERES (B,C,D) | 14/20RES(L) 20RESB 20RESD | 8.5/12RES(L) 15/30RES/RESA 15/30RYG/REYG 17/18RES(L) | 14/20RESA 20RESC (240 Volts) | 8/10/12RESV(L) 14/20RESA(L) 20RESC(L) (120 Volts) |
| Volts | 120 | 120 | 120 | 120 | 240 | 120 |
| Heater pad rating, Watts | — | 30 | 30 | 31 | — | — |
| Heater wrap rating, Watts | 80 | | | 50 | | |
| Thermostat on temperature | 18°C (65°F) | | | 18°C (65°F) | | |
| Thermostat off temperature | 27°C (80°F) | | | 27°C (80°F) | | |
| Battery wrap length, mm (in.) | 1118 (44) | | | 711 (28) | | |
| Power cord length, mm (in.) | 1676 (66) | | | 1829 (72) | | |

DISTRIBUTED BY:

Availability is subject to change without notice. Kohler Co. reserves the right to change the design or specifications without notice and without any obligation or liability whatsoever. Contact your local Kohler® generator distributor for availability.

© 2013, 2014, 2015, 2016 by Kohler Co. All rights reserved.